

Product datasheet

Specifications



TeSys Integral - undervoltage trip - 240 V AC 50 Hz - without time delay

LA1LC072U

⚠ Discontinued on: 1 Nov 2020

⚠ Discontinued

Main

Range	TeSys
Device short name	LA1LC
Product or component type	Undervoltage trip
Product compatibility	LD4 LD5
Range compatibility	TeSys TeSys Integral contactor breaker

Complementary

[Uc] control circuit voltage	240 V AC 50 Hz
Time delay	Without time delay
Voltage release type	Undervoltage release Instantaneous
Control circuit voltage limits	0.8...1.1 Uc
Threshold tripping voltage	0.35...0.7 Uc
Inrush power in VA	8 VA AC
Hold-in power consumption in VA	4 VA AC
Quantity per set	Set of 10
Net weight	0.15 kg

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	4.4 cm
Package 1 Width	6.3 cm
Package 1 Length	11.5 cm
Package 1 Weight	134 g

Contractual warranty

Warranty (in months)	18
----------------------	----



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Longer



Lifetime extension

Repair

No