

Product datasheet

Specifications

TeSys Integral - undervoltage trip - 0.2 s



LA1LC070EJ

⚠ Discontinued on: 1 Nov 2020

⚠ Discontinued

Main

Range	TeSys
Device short name	LA1LC
Product or component type	Undervoltage trip
Product compatibility	LD4 LD5
Range compatibility	TeSys TeSys Integral contactor breaker

Complementary

Time delay	0.2 s
Voltage release type	Undervoltage release
Control circuit voltage limits	0.8...1.1 U _c
Threshold tripping voltage	0.35...0.7 U _c
Inrush power in VA	8 VA AC
Hold-in power consumption in VA	4 VA AC
Quantity per set	Set of 10
Net weight	0.15 kg

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	4 cm
Package 1 Width	5 cm
Package 1 Length	11.5 cm
Package 1 Weight	0.17 kg

Contractual warranty

Warranty (in months)	18
----------------------	----

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Longer



Lifetime extension

Repair

No