

Product data sheet

Specifications



coil LX1-LC - 36 V AC 60Hz

LX1LC030

! Discontinued

Main

Range	TeSys
Device short name	LX1
Product or Component Type	Coil
[Uc] control circuit voltage	30 V AC 50 Hz 36 V AC 60 Hz
Power consumption in VA	12...18 VA AC 0.3 60 Hz sealed 170...230 VA AC 0.55 60 Hz inrush
Value of inductance	0.107 mH closed circuit
Average resistance	2.925 Ohm +/- 10 %

Complementary

Range compatibility	TeSys LX1 contactor
Net Weight	0.26 lb(US) (0.12 kg)

Ordering and shipping details

Category	18402-WORLD SERVICE PARTS(CONTROL ACCESS)
Discount Schedule	CP10
GTIN	3389110246308
Returnability	No

Contractual warranty

Warranty (in months)	18
----------------------	----

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Longer

Lifetime extension	
Repair	No