

Product datasheet

Specifications

extra neutral bar for distribution terminal block - 40 A



13516

⚠ Discontinued on: 12 May 2023

⚠ Discontinued

Main

Range of product	Prisma PH Prisma GX Prisma P Prisma G Canalis KV
Product or component type	Extension module
Comb busbar, distribution terminal block accessory type	Neutral bar
Poles description	1N
Accessory / separate part category	Connection accessories

Complementary

Distribution block outgoers	4 x 13 holes
Mounting support	35 mm symmetrical DIN rail Multifix rail
[Ie] rated operational current	40 A
[Ui] rated insulation voltage	500 V AC
[Icw] rated short-time withstand current	3.5 kA for 1 s
[Ipk] rated peak withstand current	20 kA
Busbar length	89 mm
Kit composition	Cover Insulating back Open screws
Connections - terminals	Cable6...16 mm² semi-rigid
Product compatibility	Pragma C12 modular enclosures Pragma D18 modular enclosures Pragma F24 modular enclosures All enclosures Prisma functional enclosures

Environment

Standards	EN 60947-7-1
Pollution degree	3

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Package 1 Height	0.6 cm
Package 1 Width	0.9 cm
Package 1 Length	8.8 cm
Package 1 Weight	33 g

Contractual warranty

Warranty (in months)	18
----------------------	----



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Longer

Lifetime extension	
Repair	No

Use Again

Repack and remanufacture	
End of life manual availability	No need of specific recycling operations
WEEE Label	 The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins