

# Product datasheet

Specifications



## P111 basic - no BI 6BO - Ion 1/5A 0.01-2Ion - Vx 24-240VAC/250VDC

REL10020

⚠ Discontinued on: 30 Jun 2021

⚠ End-of-service on: 4 Apr 2023

⚠ Discontinued

## Main

Range of product	MiCOM P11x
Device short name	P111N
Relay application	Feeder
Protection type	ANSI 86 : lockout ANSI 49RMS : thermal overload protection ANSI 50N/51N : earth fault ANSI 50BF : breaker failure ANSI 50/51 : phase overcurrent ANSI 46 : negative sequence/unbalance
communication protocol	Modbus RTU by RS485 in rear IEC 60870-5-103 by USB in front
Input output max capacity	0 inputs + 6 outputs
Communication port protocol	IEC 60870-5-103 Modbus RTU

## Complementary

Type of measurement	Current
auxiliary supply	24...240 V AC 250 V DC
[Us] rated supply voltage	24...60 V DC 19...72 V 24...60 V AC 19...66 V 90...240 V AC 71...265 V 60...250 V DC 48...300 V
Control and monitoring type	Latching/acknowledgement Switching of groups of settings
Metering type	Phase currents
Network and machine diagnosis type	Fault recording Event recording Disturbance recording 6 s
Display type	LCD display: 2 lines of 16 characters ASCII (European characters) and 9 key
earth current inputs	1/5 A 0.01...2 Ion
Communication port support	RS485 USB

## Environment

Device mounting	Flush
Mounting mode	Flush-mounted

## Packing Units

<b>Unit Type of Package 1</b>	PCE
<b>Number of Units in Package 1</b>	1
<b>Package 1 Height</b>	16.5 cm
<b>Package 1 Width</b>	16.5 cm
<b>Package 1 Length</b>	22.5 cm
<b>Package 1 Weight</b>	882.0 g
<b>Unit Type of Package 2</b>	S04
<b>Number of Units in Package 2</b>	6
<b>Package 2 Height</b>	30.0 cm
<b>Package 2 Width</b>	40.0 cm
<b>Package 2 Length</b>	60.0 cm
<b>Package 2 Weight</b>	6.058 kg

## Contractual warranty

<b>Warranty (in months)</b>	18
-----------------------------	----



## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Use Longer



#### Lifetime extension

Repair

No