

Product datasheet

Specifications



Long time rating plug, low setting H,
0.48 to 0.64 x In

48840

Main

Product or component type	Rating plug
Device short name	long time rating plug low setting H
Device application	Control
Range compatibility	MasterPact NT circuit breaker

Complementary

Long time pick-up adjustment type Ir	Adjustable
Long time pick-up adjustment range	0.48...64 x In

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	3.000 cm
Package 1 Width	8.000 cm
Package 1 Length	3.500 cm
Package 1 Weight	11.000 g
Unit Type of Package 2	BB1
Number of Units in Package 2	20
Package 2 Height	9.000 cm
Package 2 Width	18.000 cm
Package 2 Length	13.000 cm
Package 2 Weight	260.000 g
Unit Type of Package 3	S03
Number of Units in Package 3	240
Package 3 Height	30.000 cm
Package 3 Width	30.000 cm
Package 3 Length	40.000 cm
Package 3 Weight	3.607 kg

Contractual warranty

Warranty (in months)	18
----------------------	----

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better

Materials and Substances	
Packaging made with recycled cardboard	Yes
Packaging without single use plastic	No, we have minimized the use of plastic in the packaging in compliance with regulations and considering quality and safety standards
SCIP Number	Ce203ae2-c7e0-4aad-aa17-1e7ab31e4934
EU RoHS Directive	Compliant By Exemption
REACH Regulation	Reference contains Substances of Very High Concern above the threshold
Halogen-free status	Product contains halogen above thresholds
PVC free	Yes

Use Longer

Lifetime extension	
Repair	No

Use Again

Repack and remanufacture	
Take-back	No