

Product data sheet

Specifications

SQUARE D



TeSys NEMA Sz 5 open starter, 3P, 120 VAC

T36GN13G7S

! Discontinued on: Jun 30, 2020

! Discontinued

Main

Product	Starter
Range of Product	TeSys N
Current Rating	270 A
Certifications	UL Listed CSA
Control Circuit Type	Separate control circuit
Enclosure Type	Not rated (open device)
Auxiliary Contacts	1 NO
Horsepower Rating	75 HP 200 V AC 100 HP 230 V AC 200 HP 460 V AC 200 HP 575 V AC
Number of Poles	3P
Phase	3 phase
Maximum Voltage Rating	600 V AC
NEMA Size	5
Control Circuit Voltage	120 V AC
Starter Type	Non reversing
Electrical Connection	Lugs ordered separately
Overload Type	Solid state Motor Logic class 10/20 90...270 A

Ordering and shipping details

Category	21199-TESYS N STARTERS SIZES 3 - 7
Discount Schedule	CP1
Returnability	No
Country of origin	MX

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1

Contractual warranty

Warranty (in months)	18
----------------------	----

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better

Materials and Substances	
EU RoHS Directive	Compliant
California proposition 65	WARNING: Cancer and Reproductive Harm - www.P65Warnings.ca.gov

Use Longer

Lifetime extension	
Repair	No