

Product data sheet

Specifications



contactor coil, TeSys D LX1D, 277 V AC 60 Hz

LX1D8W6

 **Discontinued on:** Jul 12, 2021

Product availability: Non-Stock - Not normally stocked in distribution facility

 **Discontinued**

Main

Range	TeSys
Product or Component Type	Contactor coil
Range compatibility	TeSys TeSys D LC1D contactor
Coil type	AC 60 Hz
[Uc] control circuit voltage	277 V AC 60 Hz

Complementary

Control circuit voltage limits	0.85...1.1 Uc (at <131 °F (55 °C))
Average resistance	125.75 Ohm 68 °F (20 °C)
Inrush power in VA	300 VA 0.8 68 °F (20 °C))
Hold-in power consumption in VA	22 VA 60 Hz 0.3 68 °F (20 °C))
Mechanical durability	10 Mcycles
Product Weight	0.57 lb(US) (0.26 kg)

Environment

Ambient air temperature for operation	68 °F (20 °C)
---------------------------------------	---------------

Ordering and shipping details

Category	US10I1222341
Discount Schedule	0I12
GTIN	3389110115574
Returnability	No

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	2.4 in (6.2 cm)
Package 1 Width	4.5 in (11.5 cm)
Package 1 Length	6.7 in (17 cm)
Package weight(Lbs)	9.9 oz (280 g)

Contractual warranty

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better



Materials and Substances

California proposition 65

WARNING: This product can expose you to chemicals including: Antimony oxide & Antimony trioxide which is known to the State of California to cause Carcinogen harm. For more information go to www.p65warnings.ca.gov

Use Longer



Lifetime extension

Repair

No