

# Product data sheet

Specifications



NEMA Contactor, TeSys N,  
reversing, Size 0, 18A, 5HP at  
460VAC, 3 pole, 3 phase, 24VAC  
50/60Hz coil, open

T02BN23B7

! Discontinued

! Discontinued on: Nov 11, 2020

! End-of-service on: Dec 31, 2020

**Product availability: Non-Stock - Not normally stocked in  
distribution facility**

## Main

Product Type	Contactors
Range	TeSys N
Contactors Type	Reversing
NEMA Size	0
Motor Horsepower Rating HP	3 hp 200 V AC 3 hp 230 V AC 5 hp 460 V AC 5 hp 575 V AC

## Complementary

Rated Current	18 A
[Ue] Rated Operational Voltage	600 V AC
Control Circuit	Common control circuit
Coil Voltage	24 V AC
Number of Poles	3P
Network Phases	3 phase
Auxiliary Contact Composition	1 NO + 1 NC
Electrical Connection	Screw clamp terminals

## Environmental

Product Certifications	UL Listed CSA
NEMA Degree of Protection	Not rated (open device)

## Ordering and shipping details

Category	US10CP121196
Discount Schedule	0CP1
GTIN	3606480573200
Returnability	No

## Packing Units

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

<b>Unit Type of Package 1</b>	PCE
<b>Nbr. of units in pkg.</b>	1
<b>Package 1 Height</b>	4.7 in (12 cm)
<b>Package 1 Width</b>	4.7 in (12 cm)
<b>Package 1 Length</b>	5.6 in (14.2 cm)
<b>Package weight(Lbs)</b>	2.061 lb(US) (0.935 kg)

## **Contractual warranty**

<b>Warranty (in months)</b>	18
-----------------------------	----



## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Use Better



#### Materials and Substances

[EU RoHS Directive](#)

Compliant

California proposition 65

WARNING: Cancer and Reproductive Harm - [www.P65Warnings.ca.gov](http://www.P65Warnings.ca.gov)

PVC free

Yes

### Use Longer



#### Lifetime extension

Repair

No

### Use Again



#### Repack and remanufacture

[Circularity Profile](#)

[End of Life Information](#)