

Product datasheet

Specifications



Auxiliary contact 1 NO standard - for Fupact INF32 to 800

49609

⚠ Discontinued on: 12 Feb 2021

EAN Code: 3303430496090

⚠ Discontinued

Main

Range of product	INF32 INF100...160 INF40 INF63 INF200...800
Range	FuPact
Device short name	auxiliary contact
Product or component type	Auxiliary contact
Device application	Connection
Range compatibility	FuPact Fupact INF fuse-switch disconnecter
Auxiliary contacts type	Standard
Signal contacts composition	1 NO
[Ith] conventional free air thermal current	16 A

Complementary

Mounting mode	Left hand side
output contact breaking capacity	AC-15: 6 A at 24 V AC 50/60 Hz AC-15: 6 A at 48 V AC 50/60 Hz DC-12: 6 A at 24 V DC AC-15: 2 A at 660/690 V AC 50/60 Hz AC-15: 3 A at 440 V AC 50/60 Hz AC-15: 4 A at 380/415 V AC 50/60 Hz AC-15: 6 A at 110 V AC 50/60 Hz AC-15: 6 A at 220/240 V AC 50/60 Hz AC-15: 6 A at 250 V AC 50/60 Hz DC-12: 0.1 A at 380/415 V DC DC-12: 0.1 A at 440 V DC DC-12: 0.4 A at 220/240 V DC DC-12: 0.4 A at 250 V DC DC-12: 1.1 A at 110 V DC DC-12: 2 A at 48 V DC
Minimum load	10 mA at 24 V

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1

Logistical informations

Country of origin	BG
-------------------	----

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Contractual warranty

Warranty (in months)	18
----------------------	----



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)



Environmental footprint

Environmental Disclosure

[Product Environmental Profile](#)

Use Better



Materials and Substances

EU RoHS Directive

[Compliant](#)

PVC free

Yes

Use Longer



Lifetime extension

Repair

No

Use Again



Repack and remanufacture

WEEE Label



The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins