

Product data sheet

Specifications



TeSys Integral - undervoltage trip - 48 V AC 50/60 Hz - 0.2 s

LA1LC070E

⚠ Discontinued on: Jul 12, 2021

⚠ Discontinued

Main

Range	TeSys
Device short name	LA1LC
Product or Component Type	Undervoltage trip
Product Compatibility	LD4 LD5
Range compatibility	TeSys TeSys Integral contactor breaker

Complementary

[Uc] control circuit voltage	48 V AC 50/60 Hz
Time delay	0.2 s
Voltage release type	Undervoltage release
Control circuit voltage limits	0.8...1.1 U _c
Threshold tripping voltage	0.35...0.7 U _c
Inrush power in VA	8 VA AC
Hold-in Power Consumption in VA	4 VA AC
Quantity per Set	Set of 10
Product Weight	0.33 lb(US) (0.15 kg)

Ordering and shipping details

Category	18402-WORLD SERVICE PARTS(CONTROL ACCESS)
Discount Schedule	CP10
GTIN	3389110181869
Returnability	No

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	1.7 in (4.3 cm)
Package 1 Width	2.5 in (6.3 cm)
Package 1 Length	4.5 in (11.5 cm)
Package weight(Lbs)	5.9 oz (166 g)

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Longer



Lifetime extension

Repair

No